

OUTDOOR PAR TRI 12 IP 65

DMX CONTROL TABLE



2-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 031	Blackout
	032 - 255	Colour macro
	032 - 063	Red
	064 - 095	Green
	096 - 127	Blue
	128 - 159	Yellow
	160 - 191	Cyan
	192 - 223	Magenta
	224 - 255	White

3-CHANNEL 1 MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 004	Blackout
	005 - 080	Colour macro
	005 - 015	Red
	016 - 026	Green
	027 - 037	Blue
	038 - 048	Yellow
CH3	049 - 059	Cyan
	060 - 070	Magenta
	071 - 080	White
	081 - 150	Colour change (rate)
	151 - 255	Colour blending (rate)

3-CHANNEL 2 MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Red (0 - 100%)
CH2	000 - 255	Green (0 - 100%)
CH3	000 - 255	Blue (0 - 100%)

6-CHANNEL MODE		
CHANNEL	VALUE	FUNCTION
CH1	000 - 255	Master dimmer (0 - 100%)
CH2	000 - 255	Stroboscope (rate 0 - 100%)
CH3	000 - 255	Red (0 - 100%)
CH4	000 - 255	Green (0 - 100%)
CH5	000 - 255	Blue (0 - 100%)

CH6	000 - 004	Blackout / colour mix CH3 - CH5
	005 - 080	Colour macro
	005 - 015	Red
	016 - 026	Green
	027 - 037	Blue
	038 - 048	Yellow
	049 - 059	Cyan
	060 - 070	Magenta
	071 - 080	White
	081 - 150	Colour change (rate)
	151 - 255	Colour blending (rate)